

CLAIMS

1. A system for monitoring wavelength division multiplexed channels in an optical signal, the system comprising:

5 a phased-array optical wavelength demultiplexer (phasar) device including an input port for receiving an input optical signal, and an output port for transmitting an optical signal, the input and output ports being connected by a waveguide array;

10 phase control means connected to receive a control signal and operable to vary the effective optical length of each waveguide in the array, such that the phase of optical signals passing through respective waveguides also vary in dependence upon that received control signal;

15 detector means connected to receive the output optical signal from the phasar device, and operable to produce a detector signal relating to that output optical signal; and

20 control means connected to receive the detector signal, and operable to supply the control signal to the phase control means, such that a signal from a desired one of the multiplexed channels is output from the phasar device to the detector means.

25 2. A system as claimed in claim 1, wherein the phase control means are provided by a heater device which acts on the waveguides in the waveguide array, thereby to vary the temperature of the waveguides.

30 3. A system as claimed in claim 1, wherein the phase control means are operable to cause an acousto-optic effect in the waveguides of the array.

4. A system as claimed in claim 1, wherein the phase control means are operable to cause an electro-optic effect in the waveguides of the array.

35 5. A system as claimed in claim 1, wherein the phase control means are operable to cause a magneto-

optic effect in the waveguides of the array.

6. A system as claimed in claim 1, wherein the phase control means are operable to cause a plasma effect in the waveguides of the array.

7. A system as claimed in claim 1, wherein the phasar device, phase control means and detector means are integrated on a single integrated device.

8. A system as claimed in claim 1, comprising compensation means for adjusting the control signal on the basis of the temperature of the phasar device.

5
10
15
20
25
30
35
40
45
50
55
60
65
70
75
80
85
90
95
100
105
110
115
120
125
130
135
140
145
150
155
160
165
170
175
180
185
190
195
200
205
210
215
220
225
230
235
240
245
250
255
260
265
270
275
280
285
290
295
300
305
310
315
320
325
330
335
340
345
350
355
360
365
370
375
380
385
390
395
400
405
410
415
420
425
430
435
440
445
450
455
460
465
470
475
480
485
490
495
500
505
510
515
520
525
530
535
540
545
550
555
560
565
570
575
580
585
590
595
600
605
610
615
620
625
630
635
640
645
650
655
660
665
670
675
680
685
690
695
700
705
710
715
720
725
730
735
740
745
750
755
760
765
770
775
780
785
790
795
800
805
810
815
820
825
830
835
840
845
850
855
860
865
870
875
880
885
890
895
900
905
910
915
920
925
930
935
940
945
950
955
960
965
970
975
980
985
990
995